

Supplemental Operations Instructions for the 52259 Leisure Bay Circuit Board

(Provided Exclusively by SpaGuts.com)

- Programmable filter cycle duration: Choices are 2, 4, 6 or 12. Default is 2 hours. Press temp, then pump to enter programming mode. Press temp to adjust, press pump to exit programming. First filter cycle turns on 1 min. after power up, second turns on 12 hours later.

- Service smart self diagnostic message display on the LED

Sensor failure detection: "Sn"

* Standby mode: "Sb"

Flow switch error detection: "FL"

High-limit detection: "OH"

- Standby mode: Press temp pad, then press light pad, press any button to reset (Optional 4 button panel only).

(Provided Exclusively by SpaGuts.com)